



Features

- » Wideband up to 12 GHz
- » Complete TX and RX Modules
- » High Dynamic Range
- » Customization Available
- » RF_{in} to RF_{out} Solution

Applications

- » Replaces Coax Cable
- » Radio Over Fiber
- » Radio Astronomy
- » Remote Antenna Sites
- » Phased Array Radar
- » EW/ECM
- » Optical Delay Lines
- » SATCOM

PHOTONIC SYSTEMS INC.

900 Middlesex Turnpike
Building 5
Billerica, MA 01821
USA

Phone: 978-670-4990

Fax: 978-670-2510

E-mail: psi.info@photonicsinc.com

www.photonicsinc.com

Description

The PSI-1600-10L Microwave Photonic Link series is a family of high-performance transmitters and receivers intended to replace coaxial cable or microwave repeaters for system application up to and beyond 12 GHz. Typically used in antenna remoting or RF/IF signal distribution applications, the PSI-1600-10L links are used in military systems, satellite communications, radio astronomy, optical delay lines, cellular/wireless systems and other RF related applications. The PSI-1601-10L link contains no RF amplifiers. The PSI-1602-10L link includes an RF pre-amplifier. The PSI-1603-10L link contains an RF post-amplifier. The PSI-1604-10L link contains both an RF pre-amplifier and RF post-amplifier.

Custom RF performance, packaging, connectors and link gain configurations are possible. **Please contact PSI with your application needs.**

RF Link Performance Summary

Parameter	PSI-1601	PSI-1602	PSI-1603	PSI-1604	Units
Operating Bandwidth	.045 - 12	0.1 - 12	0.1 - 12	0.1 - 12	GHz
Link Gain	-32	0	0	32	dB
Noise Figure	40	9	41	10	dB
Input IP3	25 / 20	-10 / -13	22 / 19	-12 / -14	dBm
Spur Free Dynamic Range	106 / 103	103 / 101	103 / 101	101 / 100	dB/Hz ^{2/3}
Gain Flatness	±3	±3	±3	±4	dB
	±0.5	±0.5	±0.5	±0.5	dB

Note: Typical RF link performance specifications measured at 5 GHz with -15 dBm RF_{in} and PSI-1600-10UR receiver module. Please see transmitter and receiver datasheets.

Ordering Information

PSI Part Number	Description
PSI-1601-10L	Microwave Photonic Link Includes: <ul style="list-style-type: none"> • PSI-1600-10UT Transmitter Module • PSI-1600-10UR Receiver Module
PSI-1602-10L	Microwave Photonic Link Includes: <ul style="list-style-type: none"> • PSI-1600-10AT Amplified Transmitter Module • PSI-1600-10UR Receiver Module
PSI-1603-10L	Microwave Photonic Link Includes: <ul style="list-style-type: none"> • PSI-1600-10UT Transmitter Module • PSI-1600-10AR Amplified Receiver Module
PSI-1604-10L	Microwave Photonic Link Includes: <ul style="list-style-type: none"> • PSI-1600-10AT Amplified Transmitter Module • PSI-1600-10AR Amplified Receiver Module

Note: See individual transmitter and receiver module data sheets for further information

Rev. 5-12